

# FORT NOVOSEL

## Environmental Document

ENV-SW002: Used Battery Management  
(21 JUNE 2024)

Approved by: *Melissa Lowlavar/Travis Farmer*

### 1.0 PURPOSE

This procedure defines the requirements for the management of used batteries on Fort Novosel. Control of environmental procedures is addressed in procedure ENV-P002: Document Control.

### 2.0 SCOPE

This procedure applies to all operations that generate, transport, and temporarily store used batteries prior to turn-in for recycling, including those activities located at facilities outside the contiguous boundary of Fort Novosel. The requirements of this procedure are applicable to all military, civilian and contract personnel at Fort Novosel.

### 3.0 DEFINITIONS

Term	Definition
90-HWCAA	Less Than 90-Day Hazardous Waste Central Accumulation Area
Accumulation Start Date (ASD)	The date the first item is placed in the container.
DOT	Department of Transportation
DPW-ENRD	Directorate of Public Works, Environmental and Natural Resources Division, located in Bldg. 1121, 334-255-0487.
HMCC	Hazardous Material Control Center, located in Bldg. 1315, 334-598-1037.
HWMP	The Fort Novosel Hazardous Waste Management Plan documents procedures to ensure each step in the "cradle-to-grave" management of wastes with hazardous characteristics is carried out in a consistent manner and in accordance with (IAW) regulatory requirements. Procedures are either referenced or included in the HWMP, as necessary, to provide documented hazardous waste management instructions, from the time of waste generation until it is transported offsite for reuse or disposal.

# FORT NOVOSEL

## Environmental Document

### ENV-SW002: Used Battery Management (21 JUNE 2024)

Term	Definition
HWSAA	Hazardous Waste Satellite Accumulation Area
IAW	In Accordance With
Recycling Center	Recycling Center, located in Bldg. 9322, 334-255-0468. DPW-ENRD Recycling program manager: 334-255-2080.
Universal Waste	Universal wastes are hazardous wastes that are subject to less stringent hazardous waste management regulations, particularly by allowing more time for accumulation of these wastes in order to facilitate appropriate recycling or disposal. Five types of waste are covered under the universal waste regulations: batteries, pesticides, mercury-containing equipment, lamps, and aerosol cans. DPW-ENRD Hazardous Waste program manager: 334-255-0487.
Used Battery	<p>A device that produced electricity and may have several primary or secondary cells arranged in parallel or series. The typical batteries that are used at Fort Novosel are:</p> <ul style="list-style-type: none"> <li>▪ Alkaline (e.g., 9-volt, D, C, AA, AAA, alkaline button) – Managed as Non-Hazardous Waste, recycled when possible.</li> <li>• Lithium, Nickel-Cadmium (NiCd), Mercuric-Oxide (button and other), Nickel-Metal Hydride (NiMH), Silver Oxide, Silver-Zinc, Zinc-Carbon, Zinc Air – Managed as Universal Waste, recycled when possible.</li> </ul> <p>Lead-Acid – Managed as one-for-one exchange for recycling or turned in as Universal Waste.</p>

# FORT NOVOSEL

## Environmental Document

### ENV-SW002: Used Battery Management (21 JUNE 2024)

#### 4.0 RESPONSIBILITIES

It is the responsibility of each unit, organization or contractor working on Fort Novosel to follow these procedures.

#### 5.0 PROCEDURE

##### 5.1 Non-Hazardous Used Batteries

5.1.1 Used single-use dry cell Alkaline batteries rated up to 9-volts (e.g., 9-volt, D, C, AA, AAA, alkaline button) will be managed as Non-Hazardous Waste.

5.1.2 Non-Hazardous used dry cell Alkaline batteries will be collected and segregated from Universal Waste batteries (e.g., Lithium, Mercury, NiCd) and Lead-Acid batteries in separate containers.

##### 5.1.3 Accumulating Used Non-Hazardous Batteries

5.1.3.1 Each unit, organization or contractor must collect the used dry cell Alkaline batteries in a DOT approved container with a closing lid.

5.1.3.2 The spent, dry cell Alkaline batteries are not required to be individually segregated. They may simply be containerized in a DOT approved container. See U.S. Department of Transportation Pipeline and Hazardous Materials Safety Administration clarification letters dated 25 November 2009 (Ref. No. 09-0194 and Ref. No. 09-0090R) for additional information regarding this Non-Hazardous/Non-Regulated Waste.

5.1.3.3 The unit, organization or contractor will ensure each container has the proper label affixed. The label must identify the contents to be accumulated in the container. The label must meet the following requirements:

- All labels must be visible on the container
- All labels must be right side up
- All labels must contain the words:
  - “Non-Hazardous Waste”
  - “Used Batteries”

5.1.4 The unit, organization or contractor is to coordinate turn-in of used batteries in excess

# FORT NOVOSEL

## Environmental Document

### ENV-SW002: Used Battery Management (21 JUNE 2024)

of one 5-gallon container with the HMCC Customer Service Representative at 334-598-1037. Following review by the HMCC, large quantities of batteries must be safely prepared for transport and should be taken to the Fort Novosel Recycling Center (Bldg. 9322, 334-255-0468).

- 5.1.5 HMCC personnel will remove the lid of each container before accepting batteries. Used batteries that have not been properly segregated will not be taken.
- 5.1.6 All containers holding used batteries are to be maintained, closed (as defined by the container manufacturer), labeled, and in good condition. Spill equipment is to be near the used battery accumulation site. Management of these used battery accumulation areas is to be IAW the Installation's HWMP at all times.

## 5.2 Universal Waste Batteries

- 5.2.1 Used Lithium, Nickel Cadmium (NiCd), Mercuric-Oxide (button and other), NiMH, Silver Oxide, Silver-Zinc, Zinc-Carbon, and Zinc Air batteries will be managed as Universal Waste.
- 5.2.2 The following example common battery types and uses were described in a DOT interpretation letter dated 14 October 2008 (Ref. No. 08-0202).
  - Lithium-manganese dioxide batteries - phones and digital cameras
  - Lithium-ion button batteries - watches and calculators
  - Nickel-Cadmium batteries (dry) - power tools, toys, and cordless phones
  - Nickel-Cadmium batteries (wet) - portable electronics, toys, flashlights
  - Silver oxide batteries - common in watches

### 5.2.3 Accumulating Universal Waste Batteries

5.2.3.1 Universal Waste batteries (e.g., Lithium, NiCd, Mercuric-Oxide, Nickel Metal-Hydride (NiMH), Silver Oxide, Silver-Zinc, Zinc-Carbon, and Zinc Air batteries) will be collected in DOT approved containers with a closing lid.

5.2.3.2 Units, organizations or contractors are responsible for ensuring that all used batteries are properly segregated to prevent short-circuiting during storage and transportation. Additional details are available in 49 CFR 173. Universal Waste batteries will be segregated by one of the following methods:

# FORT NOVOSEL

## Environmental Document

### ENV-SW002: Used Battery Management (21 JUNE 2024)

- placing batteries in the original inner package;
- taping the positive end of the batteries; or,
- by using plastic “baggies” to separate individual batteries

5.2.3.3 The unit, organization or contractor will ensure each container has the proper label affixed. The label shall meet the following requirements:

- All labels must be visible on the container
- All labels must be right side up
- All labels must contain:
  - the words "UNIVERSAL WASTE",
  - the words “Used Battery(ies)”, or “Universal Waste Battery(ies)”, or “Waste Battery(ies)”, and
  - the accumulation start date (ASD) (the date the first used battery was placed in the container).

5.2.3.4 All containers holding used batteries are to be maintained, kept closed (as defined by the container manufacturer), labeled, and in good condition. Spill equipment is to be near the used battery accumulation site. Management of these used battery accumulation areas is to be IAW the Installation's HWMP at all times.

#### 5.2.4 Turning In Universal Waste Batteries

5.2.4.1 Universal Waste batteries must be turned in within six months of the ASD, regardless of full or not. Containers must be properly labelled and in good condition with all batteries segregated as described above.

5.2.4.2 HMCC and the Recycling Center personnel will remove the lid of each container before accepting batteries. Used batteries that have not been properly segregated or properly packaged will not be taken.

5.2.4.3 The unit, organization or contractor is to coordinate the turn-in of Universal Waste batteries in excess of one 5-gallon container with the HMCC Customer Service Representative at 334-598-1037. Following review by the HMCC, large quantities of Universal Waste batteries must be safely prepared for transport and should be taken to the Fort Novosel Recycling Center (Bldg. 9322, 334-255-0468).

# FORT NOVOSEL

## Environmental Document

### ENV-SW002: Used Battery Management (21 JUNE 2024)

#### 5.3 Lead-Acid Batteries

##### 5.3.1 Recycling Used Lead-Acid Batteries in the one-for-one Exchange Program

5.3.1.1 Units, organizations or contractors will recycle used Lead-Acid batteries using the one-for-one Exchange Program when possible. This program provides a one-for-one exchange of new Lead-Acid batteries for unserviceable Lead-Acid batteries.

5.3.1.2 Both new and used Lead-Acid batteries should be stored in covered areas on pallets or in a covered spill containment pallet.

5.3.1.3 The one-for-one exchange program vendor supplies new batteries to organizations and picks up any used batteries that have been collected.

5.3.1.4 The vendor takes the entire Lead-Acid battery (including the electrolyte solution).

5.3.1.5 Lead-Acid batteries in the one-for-one exchange program do not need to be labeled.

5.3.1.6 Draining batteries before collection is not necessary.

5.3.1.7 Although Lead-Acid batteries are not managed as Universal Waste, the unit, organization or contractor should not accumulate the batteries for an extended period of time and should implement a method to demonstrate how long the Lead-Acid batteries have been stored between shipments.

5.3.1.8 A battery acid spill kit is to be near the used Lead-Acid battery accumulation site. Management of these used battery accumulation areas is to be IAW the Installation's HWMP at all times.

##### 5.3.2 Recycling Used Lead-Acid Batteries as Universal Waste

5.3.2.1 Units, organizations or contractors are responsible for ensuring that used Lead-Acid batteries are properly recycled when the one-for-one Exchange Program is not utilized.

5.3.2.2 The unit, organization or contractor is to coordinate the turn-in of used Lead-Acid batteries with the HMCC Customer Service Representative at 334-598-1037 or the Recycling Center (Bldg. 9322, 334-255-0468).

5.3.2.3 Both new and used Lead-Acid batteries should be stored in covered areas on pallets or in a covered spill containment pallet.

5.3.2.4 The unit, organization or contractor will ensure each container has the

# FORT NOVOSEL

## Environmental Document

### ENV-SW002: Used Battery Management (21 JUNE 2024)

proper label affixed to each battery or to the pallet containerizing the lead-acid batteries. The label shall meet the following requirements:

- All labels must be visible on the container
- All labels must be right side up
- All labels must contain:
  - the words "UNIVERSAL WASTE",
  - the words "Used Battery(ies)", or "Universal Waste Battery(ies)", or "Waste Battery(ies)", and
  - the accumulation start date (ASD) (the date the first used battery was placed in the container).

5.3.2.5 Universal Waste lead-acid batteries must be turned in within six months of the ASD.

5.3.2.6 The unit, organization or contractor is to coordinate the turn-in of Universal Waste batteries in excess of 15 used Lead-Acid batteries with the HMCC Customer Service Representative at 334-598-1037. Following review by the HMCC, large quantities of Universal Waste Lead-Acid batteries must be safely prepared for transport and should be taken to the Fort Novosel Recycling Center (Bldg. 9322, 334-255-0468).

5.3.2.7 A battery acid spill kit is to be near the used Lead-Acid battery accumulation site. Management of these used battery accumulation areas is to be IAW the Installation's HWMP at all times.

## 5.4 Leaking or Damaged Batteries

5.4.1 Leaking or damaged Non-Hazardous and Universal Waste batteries will be segregated from intact used batteries by placing the leaking or damaged battery in a sealed plastic bag or wrapped with plastic and sealed using tape. Once sealed, the leaking or damaged battery may be placed in the appropriate collection container.

5.4.2 Lead-Acid batteries that are leaking or are damaged (e.g., cracked case) cannot be returned to the vendor as part of the one-for-one exchange program. These batteries will be accumulated in a HWSAA and turned in to the 90-HWCAA for disposal as hazardous waste.

# FORT NOVOSEL

## Environmental Document

### ENV-SW002: Used Battery Management (21 JUNE 2024)

- 5.4.3 Units, organizations and contractors will have spill equipment and training to safely and efficiently clean up minor spills and releases of battery electrolyte solutions IAW the Installation Spill Contingency Plan.
- 5.4.4 Personnel should collect the clean-up wastes in an approved non-metal container or a metal container with an appropriate liner. Wastes from the clean-up of electrolyte solution will be managed and disposed of as hazardous waste IAW the HWMP.

### 5.5 Battery Containing Equipment

- 5.5.1 If the batteries can be safely removed from the equipment, the generating unit, organization or contractors should separate the batteries and prepare appropriately by battery type for turn in to the HMCC. If the equipment is not on a hand receipt, it may be turned in to the Fort Novosel Recycling Center. Please coordinate with the Recycling Center in advance if the equipment is large.
- 5.5.2 If the batteries cannot be safely removed from the equipment and the item is not on a hand receipt, the Fort Novosel Recycling Center may accept the equipment with the batteries remaining. Batteries contained in devices must be securely installed. Batteries should be protected against short circuits (e.g., by using non-conductive caps or tape that cover the terminals entirely), damage to terminals and leakage either by design or by packaging.

### 6.0 FORMS AND RECORDS

DD Form 1348-1A, *Issue Release/Receipt Document*

Inspection Records

### 7.0 REFERENCES

ENV-P002: Document Control

40 CFR Part 273

49 CFR Parts 171-180

US DOT Battery Clarification Letters dated 14 October 2008 (Ref. No. 08-0202), 25 November 2009 (Ref. No. 09-0194 and Ref. No. 09-0090R)

DOD 4160.21-M, Chapters 4 and 10

Hazardous Waste Management Plan (HWMP)

Installation Spill Contingency Plan (ISCP)